JOCKEY PUMP CONTROLLER

DOMINATOR

OVERVIEW

All Purpose Pumps Jockey/Jacking Pump Controller is designed to provide control and status indication for a Jockey/Jacking pump, compliant with the current Australian Standards (AS 2941-2013:Section 5). Housed in a red powder coated metal enclosure.



FEATURES

- Removable cable gland plate
- Lockable mains power supply isolator switch
- IP65-rated 2 mm galvanised steel enclosure, powder-coated RAL3020 (Traffic Red)
- Control protection circuit breaker
- Automatic motor starting and control
- DOL pump motor starter
- Pump motor thermal overload protection with manual reset
- Spring return to auto selector switch
- Fitted with 2 x 10A RCBO's for both light and power distribution within a containerised system.

INDICATION

This Panel is fitted with LED indication for the following:

- **Power On (GREEN)** - Indicates control supply is present within the controller.
- **Pump Running (RED)** - Indicates that the JP contactor has closed and 240V is supplied to the motor windings.
- **Pump Fault (RED)** - Indicates an overload on the jockey pump motor windings.
- **Pump Run Counter** - Indicates the pump total run counts.

VOLT FREE CONTACTS

4 × volt-free outputs as standard – Power On, Pump Run, Pump Fault, Pump Manual

	PRODUCT CODE	RATING AMPS
240V	5201047	7-10A
415V	5201048	7-10A